



FINISHES :

 High Gloss Black

 High Gloss White

 Black Ash

The Thetis 340 subwoofer is the essential part of your home theater set-up.

Versatile, it will also be an ideal complement to your stereo system. Equipped with a 25cm driver and an amplifier of 250W, it will make your experience unique and immersive.

Using a bass-reflex principle, it keeps a limited volume despite its extended performance. With a laminar port, airflow noise is significantly reduced.

The Class D amplifier drives 250 watts RMS of power, 400 Watts peak. With steep crossover slopes, matching this subwoofer to your main speakers is easy.

The Thetis subwoofers feature numerous inputs, allowing them to be associated with all types of amplifiers. They include a direct LFE input, standard RCA, and high-level inputs for amplifiers with no suitable output.

You can adjust the volume, the phase, and the frequency roll-off for a perfect fit with your main speakers.

Each Thétis subwoofer is supplied with a remote, an LED display on the front panel providing visibility of the sound setting. It also features an automatic standby/wake mode.

TYPE

Bass-Reflex

WOOFER SIZE

10 inch

PHASE

0-180 (2 positions)

BANDWIDTH (+/- 3dB)

25 Hz - 120 Hz

POWER HANDLING (Watts RMS)

250 W - Classe D

MAIN INPUT

100-240V / 50-60 Hz

INPUTS

LFE - Line IN (L/R) - Speaker IN

OUTPUTS

Speaker OUT

DISPLAY

Front panel Volume display

VOLUME

Rotating knob - IR remote

CROSSOVER CUT-OFF FREQUENCY

Rotating knob 30-120 Hz

AUTO ON / STANBY

ON/OFF

DIMENSIONS

13,4 x 13,4 x 15,1 inch

NET WEIGHT

35,5 lbs

CODE EAN

High Gloss Black : 3660216007575

High Gloss White : 3660216007582

Black Ash : 3660216007599



FINISHES :

- High Gloss Black
- High Gloss White
- Black Ash

The Thetis 300 subwoofer is the essential part of your home theater set-up.

Versatile, it will also be an ideal addition to your stereo system, for example to accompany smaller speakers. Equipped with a 20cm, downward-facing driver and an amplifier of 150W, this subwoofer in a compact format allows your set-up to considerably extend the bandwidth in the low frequencies.

Using a bass-reflex principle, it keeps a limited volume while offering surprising performance.

The Thetis subwoofers feature numerous inputs, allowing them to be associated with all types of amplifiers. They include a direct LFE input, standard RCA, and high-level inputs for amplifiers with no suitable output.

You can adjust the volume, the phase, and the frequency roll-off for a perfect fit with your main speakers.

Each Thetis subwoofer is supplied with a remote, an LED display on the front panel providing visibility of the sound setting. It also features an automatic standby/wake mode.

TYPE

Bass-Reflex

WOOFER SIZE

8,3 inch

PHASE

0-180 (2 positions)

BANDWIDTH (+/- 3dB)

32 Hz - 120 Hz

POWER HANDLING (Watts RMS)

150 W - Classe D

MAIN INPUT

100-240V / 50-60 Hz

INPUTS

LFE - Line IN (L/R) - Speaker IN

OUTPUTS

Speaker OUT

DISPLAY

Front panel Volume display

VOLUME

Rotating knob - IR remote

CROSSOVER CUT-OFF FREQUENCY

Rotating knob 30-120 Hz

AUTO ON / STANBY

ON/OFF

DIMENSIONS

11,8 x 11,8 x 13,4 inch

NET WEIGHT

23,4 lbs

CODE EAN

High Gloss Black : 3660216007605

High Gloss White : 3660216007612

Black Ash : 3660216007629